

00/01/01
393 U.S. PTO

11-13-00

A

ASSISTANT COMMISSIONER OF PATENTS AND TRADEMARKS
Washington, DC 20231

PATENT
Date: November 10, 2000
File No.: 1412.64700

Sir:

Transmitted herewith for filing is the patent application of

Inventor(s): Nimal G. Senarath
Robert Matyas
Leo L. Strawczynski

I hereby certify that this paper is being deposited with the United States Postal Service as EXPRESS MAIL in an envelope addressed to: Assistant Commissioner for Patents, Washington, D.C. 20231, on 11/10/2000

For: MULTIBEAM WIRELESS COMMUNICATIONS
METHOD AND SYSTEM INCLUDING AN
INTERFERENCE AVOIDANCE SCHEME
IN WHICH THE AREA OF EACH
TRANSMITTED BEAM IS DIVIDED
INTO A PLURALITY OF SUB-AREAS

Express Label No.: EL699921851US

Signature: James K. Folker
EXPRESS WCM
Appl. February 20, 1998

Enclosed are:

- (X) 30 pages of specification, including 27 claims and an abstract.
() an executed oath or declaration, with power of attorney.
(X) an unexecuted oath or declaration, with power of attorney.
(X) 5 sheet(s) of informal drawing(s).
() sheet(s) of formal drawings(s).
(X) Assignment(s) of the invention to Nortel Networks Limited.
(X) Assignment Form Cover Sheet.
(X) A check in the amount of \$ 40.00 to cover the fee for recording the assignment(s) is enclosed.
() Information Disclosure Statement.
() Form PTO-1449 and cited references.
() Associate power of attorney.
() Priority Document.

Fee Calculation For Claims As Filed

a) Basic Fee						\$ 710.00
b) Independent Claims	6	- 3 =	3	x \$ 80.00 =	\$ 240.00	
c) Total Claims	27	- 20 =	7	x \$ 18.00 =	\$ 126.00	
d) Fee for Multiple Claims				\$270.00 =	\$	
Total Filing Fee					\$ 1076.00	

- (X) A check in the amount of \$740.00 to cover the filing fee is enclosed.
(X) Charge \$ 336.00 to Deposit Account No. 07-2069 (for extra claims fees).
() Other _____
(X) The Commissioner is hereby authorized to charge any additional fees which may be required to this application under 37 C.F.R. §§1.16-1.17, or credit any overpayment, to Deposit Account No. 07-2069. Should no proper payment be enclosed herewith, as by a check being in the wrong amount, unsigned, post-dated, otherwise improper or informal or even entirely missing, the Commissioner is authorized to charge the unpaid amount to Deposit Account No. 07-2069. A duplicate copy of this sheet is enclosed.

Suite 8660 - Sears Tower
233 S. Wacker Drive
Chicago, Illinois 60606
(312) 993-0080

GREER, BURNS & CRAIN, LTD.

By: James K. Folker
James K. Folker
Registration No. 37,538

I hereby certify that this paper is being deposited with the United States Postal Service as EXPRESS MAIL in an envelope addressed to: Assistant Commissioner for Patents, Washington, D.C. 20231, on 11/10/2000
Express Label No.: EL699921851051
Signature: James H. Zeller
EXPRESS WCM
Appr. February 20, 1996

**MULTIBEAM WIRELESS COMMUNICATIONS METHOD AND SYSTEM
INCLUDING AN INTERFERENCE AVOIDANCE SCHEME
IN WHICH THE AREA OF EACH TRANSMITTED BEAM IS
DIVIDED INTO A PLURALITY OF SUB-AREAS**

FIELD OF THE INVENTION

The present invention relates generally to the field of wireless communications, and more particularly to multibeam wireless communications systems and methods in which interference from adjacent beams is minimized, without unduly reducing capacity, by dividing each beam area into at least two sub-areas.

BACKGROUND OF THE INVENTION

One of the many current uses of wireless communication principles is within a cellular network, such as the cellular networks employed by the increasingly popular cellular telephone systems. In such systems, the geographical area is divided into a plurality of adjoining cells, which are ideally of a hexagonal shape, such as cells 12 of a network 10 of Figure 1. Mobile units (such as cellular telephones) move about the geographical area encompassed by the cellular array, and information is transmitted to/from the mobile units from/to a base transmitter station (BTS).

One type of cellular arrangement common in North America is known as the center excitation arrangement, whereby a BTS is situated within the center of each cell. Figure 2 schematically depicts one cell 12 of a center excitation arrangement,

whereby BTS 14 transmits a downlink radiation beam into each of the three sectors 16, 18, and 20. In the Figure 2 example, each sector 16, 18, and 20 is covered by a beam with a 120° azimuth angle, so that full 360° coverage is provided by the three beams of BTS 14. It should be noted that the sectors may be divided differently, such as by having six
5 beams each having a 60° azimuth angle, twelve beams each having a 30° azimuth angle, etc., so long as the full 360° of coverage is provided by the combination of beams. It should also be noted that multiple beams may be used in each sector.

There is also a second type of excitation arrangement known as edge excitation, which is commonly used in Europe. In such an arrangement (not shown in the figures), the BTS is situated at the intersection of three cells, and beams are directed towards the center of each cell. In contrast, in the center excitation arrangement discussed above, the BTS is situated at the center of a cell, and the beams are directed outwardly from the BTS.

There is a need in cellular systems (both edge excitation and center excitation systems) to provide more capacity to transmit information over the beams to the mobile units. Theoretically, capacity gains can be realized by increasing the number of beams since each beam can carry a certain amount of information. Thus, in theory, a system using four beams per sector will have a greater capacity than one with three beams per sector.

However, the present inventors have realized that, in practice, some of the expected capacity gains are often diminished by interference received from adjacent beams. This is the case because beams are not transmitted along an exact azimuth angle, so there will be some overlap between adjacent beams. For example, referring to Figure 2, since the exact angle of 120° cannot be created, there will be some overlap between the beam of sector 16 and the beam of sector 18 around line 22. Similar beam overlap occurs
20 around line 24 between the beam of sector 18 and the beam of sector 20, as well as around line 26 between the respective beams of sectors 16 and 20. Such overlaps cause

interference that diminishes the capacity of the system below the capacity that would otherwise be expected.

For example, there is actually a loss of capacity when increasing from three beams per sector to four beams per sector due to the interference losses resulting from the beam overlaps described above. In particular, in a cell capacity simulation with adaptive modulation and coding, as well as with fast cell selection with a DVB-T code set (a Digital Video Broadcasting standard), the cell capacity per 5 MHz with three beams per sector (i.e., a 3/3 arrangement) was calculated to be 30.1 Mbps. This capacity number can be expected to increase by a factor of 4/3 to approximately 40 Mbps if a four beam per sector (4/4) scheme is used. However, with four beams per sector (4/4), the capacity dropped to 29.1 Mbps, mostly due to the overlap interference discussed above. Thus, it is desirable to find a way to increase capacity, without increasing interference.

BRIEF SUMMARY OF THE INVENTION

The present invention provides a method for reducing interference in a wireless system, and a system for performing the method. Although the proposed scheme can be employed in systems with any number of beams, the performance gain will be lower with a smaller number of beams. In the sample embodiments discussed below, four beam formers are used per sector, as well as a plurality of mobile units. The method includes the steps of transmitting beams B1, B2, B3 and B4 into first, second, third and fourth beam areas, respectively. At least two sub-areas are defined within each of the first, second, third and fourth beam areas based upon the degree of overlap with adjacent beam areas, whereby each of the beam areas includes at least one overlapping sub-area and at least one non-overlapping sub-area. It should be noted that the term "overlapping areas" refers to areas receiving excessive interference from other beams, and that a geographical relationship may or may not exist.

The method further includes coding signals of the beams B1, B2, B3 and B4 for receipt by a particular mobile unit based upon which one of the sub-areas that the particular mobile unit is located within.

If the invention is practiced with a TDM scheme (time division multiplex),
5 at least three time periods are utilized, wherein during the first time period (T1), simultaneous transmissions are made for receipt by mobile units located within sub-areas G1₁, G1₂, G1₃ and G1₄; during a second time period (T2), transmissions are made for receipt by mobile units located within sub-areas G2₁ and G2₄; and during a third time period (T3), transmissions are made for receipt by mobile units located within sub-areas G2₂ and G2₃.

If the invention is practiced with an FDM scheme (frequency division multiplex), the group of frequencies assigned to each cell is divided such that half of the frequencies (F1) serve mobile units located within sub-areas G1₁, G1₂, G1₃ and G1₄, and the other half of the frequencies (F2) serve mobile units located within sub-areas G2₁, G2₂, G2₃ and G2₄. The F2 set of frequencies is further divided into two groups, F2₁ and F2₂, with F2₁ serving G2₁ and G2₃ and F2₂ serving G2₂ and G2₄.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWINGS

Figure 1 is a schematic drawing of a cell cluster of a standard cellular network;

20 Figure 2 is a schematic representation of a cell with a center excitation arrangement;

Figure 3 is a schematic drawing of a basic cell array of the present invention;

Figure 4 is a schematic of a set of beam areas and sub-areas of the first
25 embodiment of the present invention;

Figure 5 is a time chart for the first embodiment;

Figure 6 is a schematic of a set of beam areas and sub-areas of the second embodiment of the present invention;

Figure 7 is a depiction of a scheme for use with the G2 sub-areas with the second embodiment;

Figure 8 is a variation on Figure 7; and

Figure 9 is another variation on Figure 7.

DETAILED DESCRIPTION OF THE INVENTION

There will now be described by way of example the best mode contemplated by the inventors for carrying out the present invention. In the following description, numerous specific details will be set forth in order to provide a thorough understanding of the present invention. It should be apparent to those of ordinary skill in the art that the present invention may be practiced without using these specific details. In other instances, well-known methods and structures have not been described in detail so as not to unnecessarily obscure the present invention.

Referring to Figure 3, one example of the basic cell array 100 of the present invention will be described. Figure 3 shows a plurality of cells 110 that are each divided into three 120° sectors (112, 114, 116), as known to those of ordinary skill in the art. For the purpose of illustration only, the present invention will be described using three 120° sectors that each include four downlink radiation beam patterns per sector. However, it should be noted that each cell may be sectored into other divisions (such as 30° sectors, 60° sectors, etc.), as well as having a lesser or a greater number of beams. It should also be noted that the invention will be described primarily in association with the time division multiplexing (TDM) mode of operation. However, one of ordinary skill in the art should be able to apply the concepts of the present invention to other modes of operation, such as the frequency division multiplexing (FDM) mode. One possible example of such an application has been explained in the Background Section above

In this example, each sector is served by four beams, with each beam covering a different beam area. These beam coverage areas are numbered, respectively, as beam areas 118, 120, 122, and 124. For the sake of simplicity, only one cell is shown to be divided into the full set of twelve beam areas, and one adjacent cell is shown to be partially divided into two beam areas (120, 122). However, it should be noted that all of the cells are divided into three sectors with four beams per sector for a total of twelve beam areas. Each of the beams may be formed by any conventional beamforming apparatus, such as by directional antennas that produce directional radiation beams.

While developing the present invention, the present inventors considered a reuse scheme in which half of the beams transmit at any one time, whereby interference between adjacent beams is avoided. For example, in the 2/4 reuse scheme, two of the four beams in each four beam sector transmit at a time. Thus, referring to Figure 3, the beams transmitting to areas 118 and 122 transmit during a first time period, and the beams transmitting to areas 120 and 124 transmit during a second time period. Such an alternating transmission sequence eliminates interference between adjacent beams with areas overlapping each other (both within a single cell and across adjacent cells) because adjacent beams do not transmit at the same time, and therefore the overlap is eliminated. The capacity of this 2/4 scheme was calculated to be 32.7 Mbps in a cell capacity simulation with adaptive modulation and coding, as well as with fast cell selection with a DVB-T code set, and a cell capacity per 5 MHz. These simulations, which were conducted under the same conditions as the 3/3 and 4/4 simulations discussed in the Background Section above, reveal that the 2/4 reuse scheme has a higher capacity than either the 3/3 scheme or the 4/4 scheme. However, even higher capacities are desirable.

One drawback of the 2/4 scheme is that, since each beam is being transmitted only during half of the full time period, there is no information being transmitted by that beam during half of the time (i.e., when it is in the off state). Thus, potential information transfer capability is being wasted. Accordingly, one important

aspect of the preferred embodiment of the present invention relates to a method of reducing this wasted potential by dividing the geographical area covered by each beam into sub-areas.

Referring now to Figures 3 and 4, a first preferred embodiment of the present invention will be described. By way of example only, the description will relate to a TDM system having a beam array configured with a re-use factor of 1 (for a reuse factor of n, the beam array is divided into n beam clusters). However, it is contemplated that the concepts of the present invention can be applied to arrays with other re-use factors, as well as to other types of cellular systems, such as an FDM system.

Figure 3 shows that each cell 110 is divided into three sectors (112, 114, 116), and that each sector is served by four beams (with coverage areas 118, 120, 122, and 124), as with the 2/4 scheme described above. Once again, a different number of sectors, as well as a different number of beams per sector, may be utilized if desired.

Figure 4 shows an enlargement of two beam areas (from the total of twelve beam areas) in each of two adjacent cells, where the beam areas have been further divided into sub-areas. Beam areas 120 and 122 are from one cell, and beam areas 124 and 118 are from an adjacent cell. As can be seen in this figure, beam area 122 is adjacent to area 120 of the same cell, as well as being adjacent to beam area 124 of the adjacent cell. Beam area 118 is served by beam B1, beam area 124 is served by beam B2, area 120 by B3 and area 122 by B4.

An important feature of the present invention is that the mobile receiving units located within each of the beam areas (118, 120, 122, and 124) are divided into two sub-areas G1 and G2, with regard to the downlink communications assigned to the particular mobile units. Because of the non-uniform geographic distribution of signal levels and interference, G1 and G2 may not be a rigid area with a distinguished geographical location. However, in general, as can be seen from Figure 4, sub-area G1₁ is the region located in the center of radiation beam pattern 118 of beam B1, and sub-area

$G2_1$ is the region located outside of area $G1_1$, but still within beam pattern 118. Similarly, sub-area $G1_2$ is located in the center of pattern 124 of beam B2, and sub-area $G2_2$ is located outside of $G1_2$. Sub-areas $G1_3$ and $G2_3$ of beam B3 and sub-areas $G1_4$ and $G2_4$ of beam B4 are also similarly configured.

The different sub-areas G1 and G2 are chosen based upon the overlap of one beam area with an adjacent beam, which depends on both terrain characteristics and beam pattern. Sub-areas $G1_1$, $G1_2$, $G1_3$ and $G1_4$ are the non-overlapping regions, and sub-areas $G2_1$, $G2_2$, $G2_3$, and $G2_4$ are the overlapping regions. Thus, for example, sub-area $G1_1$ is the region of beam area 118 (from beam B1) that does not overlap with adjacent beam area 124 (from beam B2) and beam area 120 (from beam B3), so there will be negligible interference from adjacent beams B2 and B3. On the other hand, sub-area $G2_1$ (of beam area 118) is a region that does include a slight overlap with adjacent beam areas 124 and 120, so some interference from these adjacent beams may result.

In order to avoid interference from adjacent beams (when operating in the TDM mode), the present invention utilizes a scheme whereby the transmissions to the mobile units that are located in sub-areas G1 are separated in time from the transmissions to the mobile units located in sub-areas G2. Referring now to Figure 5, which is a chart showing the different time periods for transmission to the different sub-areas by each beam, a preferred embodiment of the interference avoidance scheme of the present invention will be explained. In this figure, the shaded areas represent time periods where transmissions to mobile units within a particular sub-area are being made. The location of a particular mobile, i.e., which sub-area it is positioned in, may be determined by any of the methods known in the art, such as by reviewing the carrier to interference ratio (C/I) of signals received by the mobile unit, by pilot measurements, etc. The location of the border between sub-area G1 and sub-area G2 may be decided upon when the system is first set-up by running a simulation, or it may be changed dynamically based upon the

loading distributions. One example of an mobile optimum assignment methodology is described below.

In the preferred embodiment, an optimum methodology to assign a mobile unit to sub-area G1 or to sub-area G2 area is based on the C/I measurement that the mobile unit experiences. The mobile unit measures C/I during 4/4 cycle (CI4), as well as during 2/4 (CI2) cycle. Depending on the code/modulation levels available in the system for dynamic rate changes, let us assume that these two C/I values will correspond to rates R4 and R2, respectively, for 4/4 cycle and 2/4 cycle (i.e., the mobile unit will receive the R4 rate if it is assigned to the G1 sub-area and the mobile unit will use the R2 rate if it is assigned to G2 sub-area.

It is advisable to assign the mobile unit to G2 sub-area only if its R2 value is larger than twice the R4 value because, during the transmission to a G2 mobile unit, only half of the beams can be used, effectively reducing the contribution to capacity by a factor two. Otherwise (if the R2 value is equal to or less than twice the R4 value), the mobile unit should be assigned to the G1 sub-area.

In a similar way, if we choose three reuse schemes, 4/4, 2/4 and 1/3, the assignment of mobiles to a corresponding sub-area (G1, G2 or G3, such as shown in Figure 6) can be done according to the following rule. Let the rate that can be supported for a given mobile unit by each scheme be R1, R2 and R3, respectively, as described above. Then, compare R1, R2/2 and R3/3, and assign the mobile unit to G1, G2 or G3, respectively, depending on whether R1, R2/2 or R3/3 is the largest.

Referring back to Figure 5, the operation of the particular beam formers during each time period will be described next. First, during time period T1, all four beams, B1, B2, B3, B4, make simultaneous transmissions, carrying information signals intended specifically for the mobile units that are located within the beam's particular sub-area G1. Thus, during time T1, beam B1 only transmits information intended for receipt by mobile units located within sub-area G1₁; beam B2 only transmits information

intended for receipt by mobile units located within sub-area $G1_2$; beam B3 only transmits information intended for receipt by mobile units located within sub-area $G1_3$; and beam B4 only transmits information intended for receipt by mobile units located within sub-area $G1_4$. Since the mobiles for the $G1$ areas are selected such that there is enough
5 'open space' between sub-areas $G1_1$, $G1_2$, $G1_3$, and $G1_4$, the signals do not overlap each other and no interference is created. One selection methodology is discussed in more detail below.

In time period T2, only beams B1 and B4 transmit, and not beams B2 and B3. Moreover, beam B1 is configured to only transmit information intended for mobile units located within sub-area $G2_1$, and beam B4 only transmits information intended for units located within sub-area $G2_4$. As can be seen in Figure 4, there is essentially no overlap between sub-areas $G2_1$ and $G2_4$, so only a slight amount of interference is possible with the transmissions made during time period T2.

Time period T3 is similar to time period T2, except the other group of beams now transmit information intended for mobiles located with their associated $G2$ sub-areas. Thus, beam B2 only transmits information intended for mobile units located within sub-area $G2_2$, and beam B3 only transmits information intended for units located within sub-area $G2_3$. In the T3 time period, as with the T2 time period, interference from adjacent beam signals is reduced because sub-areas $G2_2$ and $G2_3$ do not overlap each
10 other. The T4, T5 and T6 time periods are essentially the same as time periods T1, T2 and T3, respectively, and have been provided to show that the process preferably continues by repeating itself.

In the preferred embodiment, time period T1 is approximately twice as long as time period T2 and T3. Accordingly, the length of time in T2 plus the length in T3 equals the length in T1. Time periods T2 and T3 are preferably selected as the
15 minimum time period that can be allocated to a single user in a system. For example, in a proposed system for the CDMA2000 enhanced for data standard, this time interval

is 1.67 msec. Of course, it is contemplated that other time ranges, as well as other ratios of T1 to T2 and/or T3 may also be utilized.

Next, estimations of expectations of the performance of the present invention will be discussed. Optimally, T1, T2, T3, G1, and G2 are selected according to the following formula:

$$T1 / (T2 + T3) = N1/N2 = X ,$$

where N1 and N2 are the number of mobiles assigned to G1 and G2, respectively.

When the geographical distribution of the mobiles is not uniform, different beams will have different number of mobiles in the G1 and G2 areas, and the ratio between the overall duty cycles $T1/(T2+T3)$ needs to be chosen by averaging out the ratio $N1/N2$ over a long period of time, e.g. over more than 100 time slots. In this way, unfair allocation of time slots between the G1 mobiles and the G2 mobiles can be minimized. On the other hand, if desired, the system can provide an unfair allocation to increase capacity by increasing the duty cycle for G1 mobiles, i.e. by choosing $T1/(T2+T3) >$ average $(N1/N2)$.

When compared to the 2/4 scheme discussed above, and assuming the C/I of the mobiles were not affected when a mobile is moved from 2/4 scheme to 4/4 scheme, since the reuse of the G1 sub-areas is increased to 1, the overall capacity of a system using the embodiment described above increases by a factor of up to:

$$[X + (1 - X) \times 0.5] / 0.5 = 1 + X$$

Thus, using the formula immediately above, if $X = 0.4$, the present invention can achieve a factor of up to 1.4 times the capacity of the 2/4 scheme.

Accordingly, the total capacity can be shifted from approximately 30 Mbps (for a 2/4 scheme) to 44 Mbps with the present interference avoidance scheme.

It should be noted that the following assumption was made when deriving and calculating with the above-mentioned formulas. It was assumed that the C/I values will remain the same for all of the mobile units located in the G1 sub-areas when moved from a 2/4 scheme to a 4/4 scheme. Accordingly, the slight C/I degradations in the G1 sub-areas encountered in actual practice will lower the capacity increase in comparison to the 2/4 scheme. However, the value of X can be optimized to get maximum capacity to address this situation (i.e., by increasing X and the degradations of C/I resulting from it).

It should also be noted that the expected capacity gain may actually be higher than that calculated above, since the above-calculation does not take into account the fact that the present scheme changes the reuse of the higher C/I mobile units. Since the average data rate of these mobile units is greater than the average data rate of the low C/I mobile units in a system employing adaptive coding/modulation, the overall capacity gain can be larger.

In addition, if a multi-user detection (MUD) scheme is applied to the present invention, there should be a greater increase in capacity than that found in a 2/4 scheme (which rose from 32.7 to 55.6 Mbps when a MUD scheme was applied). This is the case because of the lower levels of interference present in the 2/4 scheme.

In accordance with another aspect of the present invention, the static interference avoidance technique described above for use with a TDM scheme can also be applied with an FDM scheme. Such a system will be briefly explained while referring back to Figure 4. When the present invention is applied with a FDM scheme, the frequencies being transmitted within each cell are divided into two groups -- one group for the mobile units in the G1 sub-areas and a second group for the mobile units in the G2 sub-areas, and this second group is again divided in half, with one sub-group of

frequencies being allocated to the G_{2_1} and G_{2_4} sub-areas and the other sub-group being allocated to the G_{2_2} and G_{2_3} sub-areas. Thus, half of the frequencies allocated to the cell are transmitted for receipt by mobile units located within sub-areas G_{1_1} , G_{1_2} , G_{1_3} and G_{1_4} ; one quarter of the frequencies are transmitted for receipt by mobile units located within sub-areas G_{2_1} and G_{2_4} ; and the final quarter of the frequencies are transmitted for receipt by mobile units located within sub-areas G_{2_2} and G_{2_3} . In the FDM scheme, all of the frequencies are being transmitted at all times, unlike the TDM scheme in which the G_2 sub-areas are only served for a half or other designated portion of the total time.

As a further modification, the present invention can also be applied to a scheme that is somewhat of a hybrid of the FDM and the TDM schemes. In such a hybrid scheme, half of the frequencies are allocated to the G_1 sub-areas for transmission at all times (like a pure FDM scheme). The other half of the frequencies are allocated to all of the G_2 sub-areas (and are not divided in half again, as in the pure FDM scheme). The half of the frequencies allocated to G_2 sub-areas are alternately transmitted for receipt by either the mobile units located within sub-areas G_{2_1} and G_{2_4} , or for receipt by the mobile units located within sub-areas G_{2_2} and G_{2_3} . Accordingly, with this hybrid TDM/FDM scheme, there are essentially only two primary time periods (compared with the three primary time periods with TDM), a first time period where mobile units within sub-areas G_{1_1} , G_{1_2} , G_{1_3} , and G_{1_4} are served, as well as those in sub-areas G_{2_1} and G_{2_4} ; and a second time period where mobile units within sub-areas G_{1_1} , G_{1_2} , G_{1_3} , and G_{1_4} are again served, as well as those in sub-areas G_{2_2} and G_{2_3} .

Figure 6 shows a second embodiment of the present invention, wherein this embodiment includes a third sub-area G_3 , in addition to the two sub-areas G_1 and G_2 described above. For this embodiment, the primary discussion will relate to the present interference avoidance technique as utilized with an FDM scheme, with a brief section discussing its utilization with a TDM scheme.

In this embodiment, the three sub-areas G1, G2 and G3 are divided in the following manner. The G1 sub-areas are those sub-areas where there is one primary beam signal (such as the B1 signal for sub-area G1₁), and all of the other signals in that sub-area are of a lower power than a certain threshold power level Y1 (dB). The value of Y1 (and Y2, which is mentioned below), for example, can be between 1 dB and 10 dB, depending on the code/modulation levels available. Y1 (and Y2) are preferably pilot power levels, since it is difficult to do comparisons with C/I values. Thus, the G1 sub-areas are the centers of each of the respective beams, and they are those areas of the highest power.

The G2 sub-areas are those sub-areas where the adjacent beams from the same cell site are relatively strong, but the beams from the adjacent cells are relatively weak. In the G2 sub-areas, the difference between the power levels from one beam to an adjacent beam (from the same cell) is less than a certain threshold power level Y2 (dB), and the power of both of these two beams should be higher than the power of the beams from the adjacent cells, at least by a certain threshold, Y3, where Y2 and Y3 are preferably different from the threshold value Y1 mentioned above. The G3 sub-areas are the sub-areas where the adjacent beams from different cells are relatively strong. In the G3 sub-areas, the difference between the power levels from one beam to a beam from the adjacent cell is less than the threshold Y3 (dB).

In FDM operation, the frequencies allotted to a particular cell are divided into three groups to serve three areas, G1, G2, and G3. The mobiles in the G1 sub-areas are always served with their group of assigned frequencies, and simultaneous transmissions from all of the beams are permitted at all times without any restriction from the other transmissions in the G2 and G3 sub-areas.

The mobiles in the G3 sub-areas are served by a 2/4 pattern with a reuse factor of two. More particularly, half of the G3 frequency spectrum (i.e., one quarter of the cell's full spectrum) is simultaneously transmitted for receipt by mobile units in the

G3₁ and the G3₄ sub-areas, while the other half of the G3 spectrum is also simultaneously being transmitted for receipt in the G3₂ and G3₃ sub-areas.

For serving the mobile units in the G2 sub-areas, any one of the following three schemes may be utilized. The first scheme is depicted in Figure 7, which is a schematic of a full cell with a basic 2/4 reuse pattern for the G2 sub-areas. More specifically, with this first scheme, the frequencies assigned to the G2 sub-areas are divided in half, with one half designated as G2A and the other half designated as G2B. Thus, in this example that includes three 120° sectors with four beams per sector, half of the G2 spectrum is simultaneously used twelve times within each cell. Thus, the efficiency of G2 spectrum usage is 0.5 since the reuse factor is 2. Accordingly, if the equivalent throughput in the spectrum allocated to the G2 sub-areas is designated as "g2", then the aggregate throughput per cell equals 12 x 0.5 x g2, which can be reduced to 6 x g2.

The aggregate throughput per cell for the G2 sub-areas can be increased to 8 x g2 by using the second scheme, which will be termed the intelligent compact reuse scheme for the G2 sub-areas. Figure 8 is a schematic of a full cell under this second scheme. Once again, the frequency spectrum assigned to the G2 sub-areas is divided in half (G2A and G2B). However, under this scheme, some of the beams have both halves of the G2 spectrum assigned to them (i.e., both G2A and G2B), and some only have half of the G2 spectrum assigned to them (either G2A or G2B).

In the intelligent compact reuse scheme operation, one of the four beams in each sector is assigned both halves of the G2 frequency spectrum (G2A and G2B), with the G2 sub-area on one side of the G1 sub-area being assigned the G2A frequencies and the G2 sub-area on the other side of the G1 sub-area being assigned the G2B frequencies. Referring back to Figure 6, and taking beam area 122 as an example, the sub-area G2₄ that is below the G1₄ sub-area may be assigned the G2A spectrum, and the sub-area G2₄ that is above the G1₄ sub-area may be assigned the G2B spectrum. These assignments

are loosely represented in Figure 8 by showing that in beam area 122_x (where subscript “X” represents that these four beams are in one 120° sector, subscript “Y” represents a second sector, and subscript “Z” the third sector), G2A is shown near the right of this section, and G2A is shown near the left.

Continuing to the left from the beam area 122_x with both G2A and G2B included therein, the left side of the G2 sub-area of beam area 120_x has been assigned the G2A spectrum of frequencies. By assigning the G2A spectrum here, there will be negligible interference from overlaps with the G2 sub-area of beam area 122_x , since the far right side of the G2 sub-area of area 122_x is the G2A spectrum, and the far left side of the G2 sub-area of area 120_x is the G2B spectrum. Still continuing to the left, the right side of the G2 sub-area of area 118_x is assigned the G2B spectrum so as not to interfere with the G2A spectrum of the G2 sub-area of area 120_x . The next area, beam area 124_y (which is actually in the next sector), is similar to area 122_x in that it includes the G2A spectrum on one side of the G1 sub-area and the G2B spectrum on the other side of the G1 sub-area. In the remainder of the areas, as indicated in Figure 8, it is shown that the G2A spectrum is never directly adjacent to the G2B spectrum.

In order to avoid unfair service being allocated among the G2 sub-areas due to asymmetric allocation of the frequencies as described above, the present invention may optionally include a feature in which we propose to rotate the frequency allocation to beams in successive time slots (although this is similar to TDM, the transmissions are separated primarily based on frequencies). For example, the G2B frequencies allocated to beam 124_x will be used for 118_z in the second time slot, the G2A frequencies in 118_z will be used for 120_z , the G2A and G2B frequencies of 120_z will be used in 122_z , and so on. The capacity calculations will not be affected by this rotation of frequency allocation. It should be noted that after three time slots, the same reuse pattern will be repeated. Since this rotation is used only for inner G2 mobiles, there will be no impact upon the mobiles in the G1 and G3 sub-areas.

In the intelligent compact reuse scheme just described, the efficiency of the usage of the G2 sub-areas is increased by a factor of $4/3$ over that of the $2/4$ reuse pattern described while referring to Figure 7. With intelligent compact reuse, half of the G2 spectrum is simultaneously used sixteen times within each cell (for this example that includes three 120° sectors with four beams per sector). Accordingly, if the equivalent throughput in the spectrum allocated to the G2 sub-areas is once again designated as "g2" then the aggregate throughput per cell equals $16 \times 0.5 \times g2$, which can be reduced to $8 \times g2$ (which is an increase over the $6 \times g2$ aggregate throughput of the $2/4$ scheme of Figure 7).

The third reuse scheme for the G2 sub-areas is depicted in Figure 9, which shows a reuse pattern combined with a softer handoff scheme. With this scheme, as with the schemes of Figures 7 and 8, the G2 frequency spectrum is divided in half into frequency groups G2A and G2B. However in this case, one frequency group is assigned to the mobile units located within one G2 sub-areas of one beam and the adjacent G2 sub-area on the adjacent beam. For example, referring back to Figure 6, the G2A frequency group may be assigned to both the lower sub-area G2₄ and to the upper sub-area G2₃, which is adjacent to the lower sub-area G2₄. On the other hand, the upper sub-area G2₄, as well as the lower sub-area G2₃, will both be assigned the G2B frequency group. Thus, as shown in Figure 9, frequency group G2A alternates with frequency group G2B at the interfaces between each beam area. Since the same frequency group is used across a dividing line between beam areas, there is a softer handoff between adjacent beams since a particular mobile will be simultaneously receiving signals from two adjacent beams of the same frequency.

In the scheme of Figure 9, the efficiency of G2 usage is 0.5 because the reuse factor is two, which is the same as the $2/4$ pattern of Figure 7. As also similar to the $2/4$ pattern, half of the G2 spectrum is simultaneously used twelve times within each cell. However, the aggregate throughput per cell of the Figure 9 scheme is higher than

that of the Figure 7 scheme due to a gain from the softer handoff. More specifically, the aggregate throughput per cell for this scheme equals $12 \times 0.5 \times g2 \times k = 6 \times g2 \times k$, where k is the softer handoff gain from the mobile unit receiving simultaneous transmissions from two different beams (where this gain, k , can be as high as 2). Accordingly, the aggregate throughput per cell for the Figure 9 scheme is expected to be higher than that of the Figure 7 scheme.

Although it will not be fully described herein, the second embodiment of the present invention (shown in Figures 6-9) can also be employed with a TDM scheme, instead of with the FDM scheme discussed above, and each of the three variations of the G2 reuse schemes described above can be applied to the TDM arrangement.

It is also contemplated that the areas can be divided into more than the three sub-areas described above, and that similar reuse groups can be identified for these sub-areas. For example, the G3 area discussed above can be subdivided into three areas, G3A, G3B and G3C, where the G3A area is the area in the middle of the G3 area, and the mobile in this area will have two strong beams (from two different cells), with all of the other beams being relatively weak. The G3B mobiles can see three relatively strong beams, with all other beams being relatively weak. Similarly, the G3C mobiles can see four or more strong beams. The reuse factor of these areas should be higher as the number of interferers are large. On the other hand, these mobiles can benefit more from the soft handoff described above, and such a design should be relatively straightforward.

While particular embodiments of the present interference avoidance techniques have been shown and described, it will be appreciated by those skilled in the art that changes and modifications may be made thereto without departing from the invention in its broader aspects and as set forth in the following claims.

What is claimed is:

1. A wireless communications system comprising:

at least four beam formers arranged within a cellular communications network, said beam formers including a first beam former for transmitting a first beam (B1) into a first area and a second beam former for transmitting a second beam (B2) into a second beam area, where said second beam area is adjacent said first beam area, and a third beam former for transmitting a third beam (B3) into a third beam area and a fourth beam former for transmitting a fourth beam (B4) into a fourth beam area, where said fourth beam area is adjacent said third beam area;

a mobile switching center for controlling signals transmitted from said at least four beam formers, including sending coded signals along said beams B1, B2, B3 and B4 such that:

each of said first, second, third and fourth beam areas are effectively divided into at least two sub-areas such that said first beam area includes sub-areas $G1_1$ and $G2_1$, said second beam area includes sub-areas $G1_2$ and $G2_2$, said third beam area includes sub-areas $G1_3$ and $G2_3$, and said fourth beam area includes sub-areas $G1_4$ and $G2_4$; and

wherein during a first time period (T1), simultaneous transmissions are made for receipt by mobile units located within sub-areas $G1_1$, $G1_2$, $G1_3$ and $G1_4$;

during a second time period (T2), transmissions are made for receipt by mobile units located within sub-areas $G2_1$ and $G2_4$; and

during a third time period (T3), transmissions are made for receipt by mobile units located within sub-areas $G2_2$ and $G2_3$.

2. The wireless communications system according to Claim 1, wherein said sub-areas $G1_1$, $G1_2$, $G1_3$ and $G1_4$ are areas with little or no interference from adjacent beams and said sub-areas $G2_1$, $G2_2$, $G2_3$ and $G2_4$ are areas with greater interference from adjacent beams.

3. The wireless communications system according to Claim 1, wherein: said sub-area $G1_1$ begins near an apex of said first area and extends generally down a center of said first area, and said sub-area $G2_1$ is located outside of said sub-area $G1_1$; and

said sub-area $G1_2$ begins near an apex of said second area and extends generally down a center of said second area, and said sub-area $G2_2$ is located outside of said sub-area $G1_2$.

4. The wireless communications system according to Claim 1 wherein said first and second areas are divided into sub-areas $G1_1$, $G2_1$, $G1_2$, and $G2_2$ based upon the carrier-to-interference ratio (C/I) of signals being received within each sub-area.

5. A wireless communications system comprising:
at least four beam formers arranged within a cellular communications network, said beam formers including a first beam former for transmitting a first beam (B1) into a first area and a second beam former for transmitting a second beam (B2) into a second beam area, where said second beam area is adjacent said first beam area, and a third beam former for transmitting a third beam (B3) into a third beam area and a fourth beam former for transmitting a fourth beam (B4) into a fourth beam area, where said fourth beam area is adjacent said third beam area;

a mobile switching center for controlling signals transmitted from said at least four beam formers, including sending coded signals along said beams B₁, B₂, B₃ and B₄ such that:

each of said first, second, third and fourth beam areas are effectively divided into at least two sub-areas such that said first beam area includes sub-areas G_{1₁} and G_{2₁}, said second beam area includes sub-areas G_{1₂} and G_{2₂}, said third beam area includes sub-areas G_{1₃} and G_{2₃}, and said fourth beam area includes sub-areas G_{1₄} and G_{2₄}; and

wherein a group of frequencies are assigned to all of said beam areas within a single cell;

further wherein said assigned group of frequencies is divided such that half of said assigned group of frequencies serve mobile units located within sub-areas G_{1₁}, G_{1₂}, G_{1₃} and G_{1₄} and the other half of said assigned group of frequencies serve mobile units located within sub-areas G_{2₁}, G_{2₂}, G_{2₃} and G_{2₄}.

6. The wireless communications system according to Claim 5, wherein: the group of frequencies assigned to sub-areas G_{2₁}, G_{2₂}, G_{2₃} and G_{2₄} is again divided in half, with one sub-group of this group being assigned to sub-areas G_{2₁} and G_{2₄} and the other sub-group being assigned to sub-areas G_{2₂} and G_{2₃}.

7. The wireless communications system according to Claim 5, said sub-area G_{1₁} begins near an apex of said first area and extends generally down a center of said first area, and said sub-area G_{2₁} is located outside of said sub-area G_{1₁}; and

said sub-area G_{1₂} begins near an apex of said second area and extends generally down a center of said second area, and said sub-area G_{2₂} is located outside of said sub-area G_{1₂}.

1 8. A method for reducing interference in a wireless system including
2 at least two beam formers and a plurality of mobile units, the method comprising the steps
3 of:

4 transmitting a first beam (B1) from a first beam former into a first area,
5 defining two sub-areas within said first area as sub-area $G1_1$ and sub-area $G2_1$;

6 transmitting a second beam (B2) from a second beam former into a second
7 area, defining two sub-areas within said second area as sub-area $G1_2$ and sub-area $G2_2$;

8 coding signals of said beams B1 and B2 for receipt by a particular mobile
9 unit based upon whether the particular mobile unit is located within said sub-area $G1_1$,
10 said sub-area $G2_1$, said sub-area $G1_2$ or said sub-area $G2_2$, such that:

11 during a first time period (T1), making simultaneous transmissions
12 from both said first and second beam formers for receipt by mobile units located,
13 respectively, within said sub-area $G1_1$, or within said sub-area $G1_2$;

14 during a second time period (T2), making transmissions from said
15 first beam former for receipt by mobile units located within said sub-area $G2_1$; and

16 during a third time period (T3), making transmissions from said
17 second beam former for receipt by mobile units located within said sub-area $G2_2$.

1 9. The method according to Claim 8, wherein:

2 said first area is adjacent to said second area;

3 said sub-area $G1_1$ begins near an apex of said first area and extends
4 generally down a center of said first area, and said sub-area $G2_1$ is located outside of said
5 sub-area $G1_1$; and

6 said sub-area $G1_2$ begins near an apex of said second area and extends
7 generally down a center of said second area, and said sub-area $G2_2$ is located outside of
8 said sub-area $G1_2$.

10. The method according to Claim 9, wherein said sub-areas G_{1_1} and G_{1_2} are each generally teardrop-shaped.

11. The method according to Claim 8, wherein said first and second areas are divided into said sub-areas G_{1_1} , G_{2_1} , G_{1_2} , and G_{2_2} based upon the carrier-to-interference ratio (C/I) of signals being received within each sub-area.

12. The method according to Claim 8, wherein a mobile unit is assigned to one of said sub-areas G_{1_1} , G_{2_1} , G_{1_2} , and G_{2_2} according to the following process:

- measuring the carrier-to-interference ratio (C/I) for a mobile unit during a 4/4 cycle to define a first rate;
- measuring the carrier-to-interference ratio (C/I) for a mobile unit during a 2/4 cycle to define a second rate; and
- comparing said first rate to said second rate, and if said second rate is larger than twice said first rate, assigning said mobile unit to said sub-area G_{2_1} for said beam B1, or to said sub-area G_{2_2} for said beam B2, otherwise said mobile unit is assigned to said sub-area G_{1_1} for said beam B1, or to said sub-area G_{1_2} for said beam B2.

13. The method according to Claim 8, further comprising:

- transmitting a third beam (B3) from a third beam former into a third area, defining two sub-areas within said third area as sub-area G_{1_3} and sub-area G_{2_3} ;
- transmitting a fourth beam (B4) from a fourth beam former into a fourth area, defining two sub-areas within said fourth area as sub-area G_{1_4} and sub-area G_{2_4} ;
- coding signals of said beams B3 and B4, such that:
- during said period T1, making simultaneous transmissions from said third and fourth beam formers for receipt by mobile units located, respectively, within said sub-area G_{1_3} or within said sub-area G_{1_4} ; and

10 during said period T2, making transmissions from said fourth beam
11 former for receipt by mobile units located within sub-area G2₄; and
12 during said period T3, making transmissions from said third beam
13 former for receipt by mobile units located within sub-area G2₃.

1 14. The method according to Claim 8, wherein said time period T1 is
2 longer than both said time period T2 and said time period T3.

15. The method according to Claim 14, wherein said time period T2 is
approximately equal in duration to said time period T3.

16. The method according to Claim 8, wherein said time periods T1, T2
and T3 are determined according to the formula $T1/(T2 + T3) = N1/N2 = X$, where N1
is the number of mobile units assigned to said sub-area G1₁ for said beam B1 or to said
sub-area G1₂ for said beam B2, N2 is the number of mobile units assigned to said sub-
area G2₁ for said beam B1 or to said sub-area G2₂ for said beam B2, and X is a
predetermined constant.

1 17. A method for reducing interference in a wireless system including
2 at least four beam formers and a plurality of mobile units, the method comprising the
3 steps of:

4 transmitting a first beam (B1) from a first beam former into a first area;
5 transmitting a second beam (B2) from a second beam former into a second
6 area;

7 transmitting a third beam (B3) from a third beam former into a third area;
8 transmitting a fourth beam (B4) from a fourth beam former into a fourth
9 area;

10 defining at least two sub-areas within each of said first, second, third and
11 fourth beam areas based upon the degree of overlap with adjacent beam areas, whereby
12 each of said beam areas includes at least one overlapping sub-area and at least one non-
13 overlapping sub-area; and
14 coding signals of said beams B1, B2, B3 and B4 for receipt by a particular
15 mobile unit based upon which of said sub-areas the particular mobile unit is located
16 within.

18. The method according to Claim 17, wherein said coding is divided
into at least three sequential time periods such that the method includes the following
additional steps:

during a first time period (T1), making simultaneous transmissions
from all four of said beam formers for receipt by mobile units located within said non-
overlapping sub-areas;

during a second time period (T2), making transmissions from said
first and fourth beam formers for receipt by mobile units located within said overlapping
sub-areas within said first and fourth areas; and

during a third time period (T3), making transmissions from said
second and third beam formers for receipt by mobile units located within said overlapping
sub-areas within said second and fourth areas.

19. The method according to Claim 17, further comprising the steps of:
defining at least a third sub-area within each of said first, second, third and
fourth beam areas based upon the degree of overlap with adjacent beam areas, whereby
each of said beam areas includes at least one non-overlapping sub-area and at least two
overlapping sub-areas, further defined as a first overlapping sub-area and a second
overlapping sub-area;

7 comparing the strength of each beam signal within a particular sub-area to
8 determine whether a particular mobile unit is located within said non-overlapping sub-
9 area, said first overlapping sub-area or said second overlapping sub-area.

1 20. The method according to Claim 19, further comprising the steps of:
2 determining that a particular mobile unit is located within said non-
3 overlapping sub-area if the strength of all beam signals but one are less than a threshold
4 value Y1;

5 determining that a particular mobile unit is located within said first
6 overlapping sub-area if the difference between signal strengths from adjacent beams is
7 less than a threshold value Y2, and the signal strength of said two adjacent beams
8 combined is greater than a threshold value Y3; and

9 determining that a particular mobile unit is located within said second
10 overlapping sub-area if the difference between signal strengths from adjacent beams is
11 less than said threshold value Y3.

12 21. The method according to Claim 20, wherein said threshold values
1 Y1, Y2 and Y3 are all different values from each other.

2 22. The method according to Claim 17, further comprising the steps of:
3 effectively dividing each of said first, second, third and fourth beam
4 areas into at least two sub-areas such that said first beam area includes sub-areas G1₁ and
5 G2₁, said second beam area includes sub-areas G1₂ and G2₂, said third beam area includes
6 sub-areas G1₃ and G2₃, and said fourth beam area includes sub-areas G1₄ and G2₄; and
7 assigning a group of frequencies to all of said beam areas within a
8 single cell;

9 dividing said assigned group of frequencies such that half of said
10 assigned group of frequencies serve mobile units located within sub-areas G1₁, G1₂, G1₃

and G1₄, and the other half of said assigned group of frequencies serve mobile units located within sub-areas G2₁, G2₂, G2₃ and G2₄.

23. The method according to Claim 17, further comprising the steps of dividing the group of frequencies assigned to sub-areas G2₁, G2₂, G2₃ and G2₄ in half again, and assigning one sub-group of this group to sub-areas G2₁ and G2₄ and assigning the other sub-group to sub-areas G2₂ and G2₃.

24. A beam forming apparatus for use with a wireless communication system, said beamforming apparatus comprising:

means for transmitting a beam into a first area and for defining two sub-areas within said first area as sub-area G1 and sub-area G2;

means for coding signals of said beam for receipt by a particular mobile unit based upon whether the particular mobile unit is located within said sub-area G1 or said sub-area G2, such that:

during a first time period (T1), making transmissions from said beam former for receipt by mobile units located within said sub-area G1, and

during a second time period (T2), making transmissions from said first beam former for receipt by mobile units located within said sub-area G2.

25. The beam forming apparatus according to Claim 24, wherein a mobile unit is assigned to one of said sub-areas G1 or G2 by:

measuring the carrier-to-interference ratio (C/I) for a mobile unit during a 4/4 cycle to define a first rate;

measuring the carrier-to-interference ratio (C/I) for a mobile unit during a 2/4 cycle to define a second rate; and

7 comparing said first rate to said second rate, and if said second rate is
8 larger than twice said first rate, assigning said mobile unit to said sub-area G2, otherwise
9 said mobile unit is assigned to said sub-area G1.

1 26. A system of signals for use in a wireless communications system
2 including at least a first beam former and a second beam former and a plurality of mobile
3 units, the signals comprising:

4 signals transmitted from the first beam former into a first area, where said
5 first area is divided into at least two sub-areas defined as sub-area G1₁ and sub-area G2₁;

6 signals transmitted from the second beam former into a second area, where
7 said second area is divided into at least two sub-areas defined as sub-area G1₂ and sub-
8 area G2₂;

9 coding said signals from said first and second beam formers for receipt by
10 a particular mobile unit based upon whether the particular mobile unit is located within
11 said sub-area G1₁, said sub-area G2₁, said sub-area G1₂ or said sub-area G2₂, such that:

12 signals transmitted during a first time period (T1) are transmitted
13 simultaneously from both said first and second beam formers for receipt by mobile units
14 located, respectively, within said sub-area G1₁, or within said sub-area G1₂;

15 signals transmitted during a second time period (T2) are transmitted
16 from said first beam former for receipt by mobile units located within said sub-area G2₁;
17 and

18 signals transmitted during a third time period (T3) are transmitted
19 from said second beam former for receipt by mobile units located within said sub-area
20 G2₂.

27. The system of signals according to Claim 26, wherein:

said first area is adjacent to said second area;

said sub-area G1₁ begins near an apex of said first area and extends generally down a center of said first area, and said sub-area G2₁ is located outside of said sub-area G1₁; and

said sub-area G1₂ begins near an apex of said second area and extends generally down a center of said second area, and said sub-area G2₂ is located outside of said sub-area G1₂.

ABSTRACT OF THE DISCLOSURE

A method for reducing interference in a wireless system, and a system for performing the method. The wireless system should include at least two, and preferably four, beam formers and a plurality of mobile units. The method includes the steps of transmitting beams B1, B2, B3 and B4 into first, second, third and fourth beam areas, respectively. At least two sub-areas are defined within each of the first, second, third and fourth beam areas based upon the degree of overlap with adjacent beam areas, whereby each of the beam areas includes at least one overlapping sub-area and at least one non-overlapping sub-area. The method further includes coding signals of the beams B1, B2, B3 and B4 for receipt by a particular mobile unit based upon which one of the sub-areas that the particular mobile unit is located within. If the invention is practiced with a TDM scheme, at least three time periods are utilized, wherein during the first time period (T1), simultaneous transmissions are made for receipt by mobile units located within sub-areas G1₁, G1₂, G1₃ and G1₄; during a second time period (T2), transmissions are made for receipt by mobile units located within sub-areas G2₁ and G2₄; and during a third time period (T3), transmissions are made for receipt by mobile units located within sub-areas G2₂ and G2₃. If the invention is practiced with an FDM scheme, the group of frequencies assigned to each cell is divided such that half of the frequencies serve mobile units located within sub-areas G1₁, G1₂, G1₃ and G1₄, and the other half of the frequencies serve mobile units located within sub-areas G2₁, G2₂, G2₃ and G2₄.




FIG. 1
(PRIOR ART)




FIG. 2
(PRIOR ART)




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9